



Compete in any market with the biggest small control panel available at a low-end price. This remarkable product is expandable to 22 zones, either through wireless or hardwire, has a superior false alarm reduction, and 60-event memory capability. The XRSuper6 is a super panel at a super low price.

XRSUPER6 COMMAND PROCESSOR™ PANEL

SYSTEM FEATURES

- Six on-board zones
- One 2-wire smoke detector zone
- Expandable to 22 zones
- Supports up to 16 wireless zones
- 16 user codes
- Supports 32-character, LCD keypads
- Access control capability
- Built-in internal clock
- Pager Direct™ paging
- User and activity checks
- Provides superior false alarm reduction features
- Expanded communications, such as Modem Ile & CID
- Arm-only user code option
- 16-character zone and area names
- 60-event memory
- Time stamped events

COMMUNICATION

The XRSuper6 surpasses the competition with its ability to communicate using a wide array of formats, including the DMP SDLC digital dialer, cellular, 4-2, CID, or Modem IIe reporting to one or two receivers.

PAGER DIRECT™

Pager Direct™ allows users to be instantly updated on the status of their security system while away from home. Pager Direct is essential for working parents wanting to confirm that their children have arrived safely home from school.

ALL/PERIMETER OR HOME/SLEEP/AWAY

Users may have their systems configured for either All/Perimeter or Home/Sleep/Away arming. All/Perimeter arming is exclusive to perimeter and interior areas, while Home/Sleep/Away arming is specifically designated to perimeter, interior, and bedroom areas. While using the Home/Sleep/Away arming, users can simply arm the perimeter and interior at night while leaving the bedroom area disarmed for accessible use. Users can maintain piece-of-mind knowing their family is protected.

HARDWARE OR WIRELESS ZONES

By simply adding the Model FA426 Wireless Receiver, users may access up to 16 zones of premise wireless protection. Easily program a wide assortment of 900MHz wireless transmitters, PIRs, glassbreaks, and smoke detectors, using an FA116 hand-held programmer. Additionally, you may include the Model 738A Ademco Wireless Interface Module to support 300MHz wireless products.

CROSS ZONING

This powerful false alarm reduction feature is unique because it only reports an alarm when two or more zones are faulted within a programmed time. For instance, if only one zone should happen to go off, a single-zone fault report is sent to the central station, indicating that only one trip was recorded at the panel.

USER CODES

Users may program up to 16 codes in the panel and have the option of assigning a standard or master authority level to control each user's level of access to the system. User code number one can also be programmed to send a silent alarm when entered at a keypad.

EVENT MEMORY

Users may maximize their accessibility by maintaining up to 60 user and time-stamped system events through the Display Events feature. In affect, event memory enables users the capability to view stored opening and closing events, zone alarms and supervisory events.

PROGRAMMABLE OUTPUTS

Four open-collector outputs are included with the XRSuper6 panel and can be used for a variety of remote control and annunciation applications. Each output is rated for 50mA maximum. Add the Model 860 Relay Output Module to provide 4 Form C relay contacts rated at 42mA.

BUILT-IN PROGRAMMER

The XRSuper6 contains an internal programmer that allows installers and service technicians to easily program and test the panel from any standard keypad.

REMOTE PROGRAMMABLE

This beneficial component provides quick and efficient remote programming for the XRSuper6 panel, using the Remote Link™ programming software. The software allows you to upload any panel program, make the necessary changes to the XRSuper6, and easily download the revised programming into the panel for greater productivity.

SECURITY COMMAND® KEYPADS

The XRSuper6 allows you to connect any number of alphanumeric and LED keypads to the panel with the ability to supervise up to 4 LCD Security Command keypads.

PANIC BUTTON KEYPADS

The DMP Security Command keypads with 2-button panic keys allow users to send police, emergency, or fire reports to the central station just by pressing two clearly labeled keypad buttons.

ACCESS CONTROL

The XRSuper6 also supports the 791 and 793 Easy Entry™ Keypads with built-in and external proximity access control readers. Users can enjoy the benefits of codeless system arming and disarming without compromising security.

LISTINGS AND APPROVALS

- CSFM 7167-1157:103
- UL S5392
 - UL 365 Police Connected Burglar
 - UL 1023 Household Burglar
 - UL 1610 Central Station Burglar
 - UL 609 Local Burglar
 - UL 1076 Proprietary Burglar
 - UL 1635 Digital Burglar
 - UL 985 Household Fire Warning

SPECIFICATIONS

Primary Power	16.5 VAC, 40 VA transformer (Model 320)
Secondary Power	12 VDC 7.0 Ah battery (Model 367)
Auxiliary Output	500mA at 12 VDC
Alarm Output	1.5 Amps at 12 VDC
Smoke Output	100mA at 12 VDC
Annunciator	
Outputs (4)	50mA each (switched ground)
Dimensions	(in 340) 12.5" X 9.5" X 2.75" (in 349) 12.25" X 11.75" X 3.125"
Enclosure	20-gauge cold-rolled steel

ACCESS CONTROL ACCESSORIES

- 733 Wiegand Interface Module
- DMP Readers and Credentials

KEYPADS

- 690 LCD
- 692 LED
- 770/771 VFD
- 790/791/793 LCD
- ePAD Virtual Keypad

ZONE EXPANDERS

- 708 Bus Extender
- 710 Bus Splitter/Repeater
- 711/711E Single zone
- 714/-8/-16 Four, 8, or 16 zone
- 715/-8/-16 Four, 8, or 16 zone

AUXILIARY DEVICES

- 300 Open Collector Harness
- 320 16.5 VAC 40 VA Wire-in Transformer
- 321 16.5 VAC 40 VA Plug-in Transformer
- 350A Attack Resistant Enclosure
- 367 12 VDC 7 Ah Battery
- 736P Popit Interface
- 738A Ademco Interface
- 860 Relay Output Module
- 865 Notification Module
- FA426 Wireless Receiver
- 895 Voice Module
- Remote Link and System Link
- Advanced Reporting
- Alarm Monitoring
- Command Center



800-641-4282

www.dmp.com

Made in the USA

INTRUSION • FIRE • ACCESS • NETWORKS

2500 North Partnership Boulevard

Springfield, Missouri 65803-8877